Installation Guide

IMPORTANT SAFETY INFORMATION

1. WARNING : RISK OF SHOCK House electric current can cause painful shock or serious injury unless handled properly. For your safety，always remember to :

A：Turn off the power supply at the fuse or circuit breaker box before you install the fixture.

B：Ground the fixture to avoid potential electric shocks and to ensure reliable starting.

C：Double-check all connections to be sure they are tight and correct.

D：Wear rubber soled shoes and work on a sturdy wooden ladder.

2. This fixture is designed for use in a circuit protected by a fuse or circuit breaker. It is also designed to be installed in accordance with local electrical codes， If you are unsure about your wiring， consult a qualified electrician or local electrical inspector， and check your local electrical code.

3. WARNING : RISK OF CUTs Some metal parts in the fixture may have sharp edges. To prevent cuts and scrapes， wear gloves when handling the parts.

4. Account for small parts and destroy packing material， as these may be hazardous to children.

Product Specification Watta.

Size	Wattage	Voltage	Cut-out	Dimension(DxH)
5″ Can	10W	~AC120V 50/60Hz	4″ Can	Φ128x21mm(FM07/08)/24mm(FM09/10)
7″ Can	12W		6″ Can	Φ178x21mm(FM07/08)/24mm(FM09/10)
9″ Can	18W		8″ Can	Φ229x21mm(FM07/08)/24mm(FM09/10)
12″ Can	24W		11″ Can	Φ305x21mm(FM07/08)/24mm(FM09/10)

Embeded in installation

4″ Can







5″/6″ Can



①Remove trim and existing lamp from recessed fixture;



②Screw E26 socket adapter into socket in the housing;



③Press the friction blade to insert the lamp into the housing and restore power.

Surface mounting installation



①Fixing bracket on terminal box;



②Connecting the wire;



③Rotate clockwise to fix the lamp;

Caution

1. WARNING : Risk of fire. Use AC120V 50/60Hz circuits

2.Suitable for damp locations. Before installing your lighting fixture，thoroughly review enclosed installation manual. If you do not have sufficient electrical wiring experience, please refer to a do-it-yourself wiring handbook or have your fixture installed by a qualified licensed electrician.All electrical connections must be in a accordance with local and National Electrical Code(NEC) standards. Reliable operating temperature is -20 to +40 degrees Celsius(-4 to+ 104 degrees Fahrenheit).

3.pls obey fire prevention regulations, do not cover the fixture with any heat insulated materials.

4.Do not change the LED light source or driver inside under any circumstance.



Note:To toggle between Standard and Nightlight modes, simply flip the light switch on (Standard),then off and back on within 5 seconds (Nightlight).

Warranty:
5 years warranty



This product is for indoor use only



For use with dimmers